



Journey 14XX Firmware Application Process Version 1.0

Description: Firmware update for all revisions of Journey 14XX Panels


Items Needed: FAT32 USB Flash Drive

Software needed: Firmware files specified in instructions

Published Date: 9/9/19

## Section 1: Firmware Revision Identification (Download of firmware files)


- 1) On the Journey 14 Panel open “Settings” then “About Device”
- 2) Locate the “Build number” and note the letters in which the it ends with.
  - a. If no letters at the end of the firmware check the panel serial number for any letters at the end



- 3) Download the appropriate firmware file.
  - a. If the Build number ends with “HW” download from the following (Or serial number has no letters at end)
    - i. <ftp://qomo08.pointto.us/J14/HW/Current/>
  - b. If the Build number ends with “GZS” download from the following (Or serial number ends with GZS)
    - i. <ftp://qomo08.pointto.us/J14/GZS/Current/>
- 4) Download the ZIP file located in the appropriate link
- 5) Once downloaded unzip to a FAT32 flash drive (2GB or larger)

## Section 2: Firmware update (NOTE: This will erase all data)

- 1) Power Off Panel
- 2) Ensure the flash drive containing firmware is inserted into one of the front USB ports.
- 3) With the unit in the powered off state, press and hold the power button until the following screen appears. (Then release power button. About 10-15 seconds)



- 4) Unit will reboot/restart itself when complete. (If unit just powers down, simply power on to resume)
- 5) Update process takes about 10-15 minutes.
- 6) Once unit boots to language choice screen select "English" and you are done.